

Serial Protocol for July 11 revision
of 232DMX LED Driver in 9600 baud mode
DIP Switch 10 ON for 9600 Baud control

Channel Control	Info
001@000	channel 1 to level 0 instantly
001@255	channel 1 to level 255 instantly

Fade control	Info
001@255F255	channel 1 to level 255 with fade time of 255 seconds (4.25 Minutes)
001@255F	channel 1 to level 255 with default fade time (currently 010 seconds)
001@STP	channel 1 stop currently running fade
001@+++	channel 1 level increment by 1 step
001@+10	channel 1 level increment by 10 steps
001@---	channel 1 level decrement by 1 step
001@-10	channel 1 level decrement by 10 steps

Multiple channel control	Info
000@255	set all channels to 255
000@STP	stop all running fades
000@255F123	fades all channels to 255 over 123 seconds

Channel Start address can be set from 1 - 64 giving control over channels 1 to 66 (Start address 64 - ch3 = channel 66)